

## **SECTION 26 2416 - PANELBOARDS**

### **PART 1 GENERAL**

#### **1.01 SECTION INCLUDES**

- A. Power distribution panelboards.
- B. Lighting and appliance panelboards.
- C. Overcurrent protective devices for panelboards.

#### **1.02 REFERENCE STANDARDS**

- A. FS W-C-375 - Circuit Breakers, Molded Case; Branch Circuit and Service 2013e (Amended 2017).
- B. NECA 1 - Standard for Good Workmanship in Electrical Construction 2015.
- C. NECA 407 - Standard for Installing and Maintaining Panelboards 2015.
- D. NEMA 250 - Enclosures for Electrical Equipment (1000 Volts Maximum) 2014.
- E. NEMA PB 1 - Panelboards 2011.
- F. NEMA PB 1.1 - General Instructions for Proper Installation, Operation and Maintenance of Panelboards Rated 600 Volts or Less 2013.
- G. NETA ATS - Acceptance Testing Specifications for Electrical Power Equipment and Systems 2013.
- H. NFPA 70 - National Electrical Code Most Recent Edition Adopted by Authority Having Jurisdiction, Including All Applicable Amendments and Supplements.
- I. UL 50 - Enclosures for Electrical Equipment, Non-Environmental Considerations Current Edition, Including All Revisions.
- J. UL 50E - Enclosures for Electrical Equipment, Environmental Considerations Current Edition, Including All Revisions.
- K. UL 67 - Panelboards Current Edition, Including All Revisions.
- L. UL 489 - Molded-Case Circuit Breakers, Molded-Case Switches and Circuit Breaker Enclosures Current Edition, Including All Revisions.

#### **1.03 ADMINISTRATIVE REQUIREMENTS**

- A. Coordination:
1. Coordinate the work with other trades to avoid placement of ductwork, piping, equipment, or other potential obstructions within the dedicated equipment spaces and working clearances for electrical equipment required by NFPA 70.
  2. Coordinate arrangement of electrical equipment with the dimensions and clearance requirements of the actual equipment to be installed.
  3. Coordinate the work with other trades to provide walls suitable for installation of flush-mounted panelboards where indicated.
  4. Verify with manufacturer that conductor terminations are suitable for use with the conductors to be installed.
  5. Notify Architect of any conflicts with or deviations from Contract Documents. Obtain direction before proceeding with work.

#### **1.04 SUBMITTALS**

- A. Product Data: Provide manufacturer's standard catalog pages and data sheets for panelboards, enclosures, overcurrent protective devices, and other installed components and accessories.
- B. Shop Drawings: Indicate outline and support point dimensions, voltage, main bus ampacity, overcurrent protective device arrangement and sizes, short circuit current ratings, conduit entry locations, conductor terminal information, and installed features and accessories.
1. Include dimensioned plan and elevation views of panelboards and adjacent equipment with all required clearances indicated.
- C. Field Quality Control Test Reports.
- D. Manufacturer's Installation Instructions: Indicate application conditions and limitations of use stipulated by product testing agency. Include instructions for storage, handling, protection, examination, preparation, and installation of product.
- E. Project Record Documents: Record actual installed locations of panelboards and actual installed circuiting arrangements.
- F. Maintenance Data: Include information on replacement parts and recommended maintenance procedures and intervals.

- G. Maintenance Materials: Furnish the following for Owner's use in maintenance of project.
  - 1. Panelboard Keys: Two of each different key.

#### **1.05 QUALITY ASSURANCE**

- A. Conform to requirements of NFPA 70.
- B. Maintain at the project site a copy of each referenced document that prescribes execution requirements.
- C. Manufacturer Qualifications: Company specializing in manufacturing the products specified in this section with minimum three years documented experience.
- D. Product Listing Organization Qualifications: An organization recognized by OSHA as a Nationally Recognized Testing Laboratory (NRTL) and acceptable to authorities having jurisdiction.

#### **1.06 DELIVERY, STORAGE, AND HANDLING**

- A. Receive, inspect, handle, and store panelboards in accordance with manufacturer's instructions and NECA 407.
- B. Store in a clean, dry space. Maintain factory wrapping or provide an additional heavy canvas or heavy plastic cover to protect units from dirt, water, construction debris, and traffic.
- C. Handle carefully in accordance with manufacturer's written instructions to avoid damage to panelboard internal components, enclosure, and finish.

### **PART 2 PRODUCTS**

#### **2.01 MANUFACTURERS**

- A. Eaton Corporation: [www.eaton.com](http://www.eaton.com).
- B. Schneider Electric; Square D Products: [www.schneider-electric.us](http://www.schneider-electric.us).
- C. Siemens Industry, Inc: [www.usa.siemens.com](http://www.usa.siemens.com).
- D. Source Limitations: Furnish panelboards and associated components produced by the same manufacturer as the other electrical distribution equipment used for this project and obtained from a single supplier.

#### **2.02 PANELBOARDS - GENERAL REQUIREMENTS**

- A. Provide products listed, classified, and labeled as suitable for the purpose intended.
- B. Unless otherwise indicated, provide products suitable for continuous operation under the following service conditions:
  - 1. Altitude: Less than 6,600 feet.
  - 2. Ambient Temperature:
    - a. Panelboards Containing Circuit Breakers: Between 23 degrees F and 104 degrees F.
- C. Short Circuit Current Rating:
  - 1. Provide panelboards with listed short circuit current rating as indicated on the drawings.
- D. Mains: Configure for top or bottom incoming feed as indicated or as required for the installation.
- E. Branch Overcurrent Protective Devices: Replaceable without disturbing adjacent devices.
- F. Bussing: Sized in accordance with UL 67 temperature rise requirements.
  - 1. Provide fully rated neutral bus unless otherwise indicated, with a suitable lug for each feeder or branch circuit requiring a neutral connection.
  - 2. Provide solidly bonded equipment ground bus in each panelboard, with a suitable lug for each feeder and branch circuit equipment grounding conductor.
- G. Conductor Terminations: Suitable for use with the conductors to be installed.
- H. Enclosures: Comply with NEMA 250, and list and label as complying with UL 50 and UL 50E.
  - 1. Environment Type per NEMA 250: Unless otherwise indicated, as specified for the following installation locations:
    - a. Indoor Clean, Dry Locations: Type 1.
    - b. Outdoor Locations: Type 3R.
  - 2. Boxes: Galvanized steel unless otherwise indicated.
    - a. Provide wiring gutters sized to accommodate the conductors to be installed.

3. Fronts:
  - a. Fronts for Surface-Mounted Enclosures: Same dimensions as boxes.
  - b. Fronts for Flush-Mounted Enclosures: Overlap boxes on all sides to conceal rough opening.
4. Lockable Doors: All locks keyed alike unless otherwise indicated.
- I. Future Provisions: Prepare all unused spaces for future installation of devices including bussing, connectors, mounting hardware and all other required provisions.
- J. Load centers are not acceptable.

### **2.03 LIGHTING AND APPLIANCE PANELBOARDS**

- A. Description: Panelboards complying with NEMA PB 1, lighting and appliance branch circuit type, circuit breaker type, and listed and labeled as complying with UL 67; ratings, configurations and features as indicated on the drawings.
- B. Conductor Terminations:
  1. Main and Neutral Lug Material: Aluminum, suitable for terminating aluminum or copper conductors.
  2. Main and Neutral Lug Type: Mechanical.
- C. Bussing:
  1. Phase Bus Connections: Arranged for sequential phasing of overcurrent protective devices.
  2. Phase and Neutral Bus Material: Copper.
  3. Ground Bus Material: Copper.
- D. Circuit Breakers: Thermal magnetic bolt-on type unless otherwise indicated.
- E. Enclosures:
  1. Provide surface-mounted or flush-mounted enclosures as indicated.
  2. Fronts: Provide door-in-door trim with hinged cover for access to load terminals and wiring gutters, and separate lockable hinged door with concealed hinges for access to overcurrent protective device handles without exposing live parts.
  3. Provide clear plastic circuit directory holder mounted on inside of door.

## **2.04 OVERCURRENT PROTECTIVE DEVICES**

- A. Molded Case Circuit Breakers:
1. Description: Quick-make, quick-break, over center toggle, trip-free, trip-indicating circuit breakers listed and labeled as complying with UL 489, and complying with FS W-C-375 where applicable; ratings, configurations, and features as indicated on the drawings.
  2. Interrupting Capacity:
    - a. Provide circuit breakers with interrupting capacity as required to provide the short circuit current rating indicated, but not less than:
      - 1) 10,000 rms symmetrical amperes at 240 VAC or 208 VAC.
      - 2) 14,000 rms symmetrical amperes at 480 VAC.
    - b. Fully Rated Systems: Provide circuit breakers with interrupting capacity not less than the short circuit current rating indicated.
  3. Conductor Terminations:
    - a. Provide mechanical lugs unless otherwise indicated.
    - b. Lug Material: Aluminum, suitable for terminating aluminum or copper conductors.
  4. Thermal Magnetic Circuit Breakers: For each pole, furnish thermal inverse time tripping element for overload protection and magnetic instantaneous tripping element for short circuit protection.
  5. Multi-Pole Circuit Breakers: Furnish with common trip for all poles.
  6. Do not use tandem circuit breakers.
  7. Provide multi-pole circuit breakers for multi-wire branch circuits as required by NFPA 70.

## **PART 3 EXECUTION**

### **3.01 EXAMINATION**

- A. Verify that field measurements are as indicated.
- B. Verify that the ratings and configurations of the panelboards and associated components are consistent with the indicated requirements.

- C. Verify that mounting surfaces are ready to receive panelboards.
- D. Verify that conditions are satisfactory for installation prior to starting work.

### **3.02 INSTALLATION**

- A. Perform work in accordance with NECA 1 (general workmanship).
- B. Install products in accordance with manufacturer's instructions.
- C. Install panelboards in accordance with NECA 407 and NEMA PB 1.1.
- D. Arrange equipment to provide minimum clearances in accordance with manufacturer's instructions and NFPA 70.
- E. Provide required support and attachment in accordance with Section 26 0529.
- F. Install panelboards plumb.
- G. Install flush-mounted panelboards so that trims fit completely flush to wall with no gaps and rough opening completely covered.
- H. Mount panelboards such that the highest position of any operating handle for circuit breakers or switches does not exceed 79 inches above the floor or working platform.
- I. Provide minimum of six spare 1 inch trade size conduits out of each flush-mounted panelboard stubbed into accessible space above ceiling and below floor.
- J. Provide grounding and bonding in accordance with Section 26 0526.
- K. Install all field-installed branch devices, components, and accessories.
- L. Multi-Wire Branch Circuits: Group grounded and ungrounded conductors together in the panelboard as required by NFPA 70.
- M. Provide filler plates to cover unused spaces in panelboards.
- N. Identify panelboards in accordance with Section 26 0553.

### **3.03 FIELD QUALITY CONTROL**

- A. Inspect and test in accordance with NETA ATS, except Section 4.
- B. Molded Case Circuit Breakers: Perform inspections and tests listed in NETA ATS, Section 7.6.1.1 for all main circuit breakers and circuit breakers larger than 100 amperes. Tests listed as optional are not required.

- C. Correct deficiencies and replace damaged or defective panelboards or associated components.

**3.04 ADJUSTING**

- A. Adjust tightness of mechanical and electrical connections to manufacturer's recommended torque settings.
- B. Adjust alignment of panelboard fronts.

**3.05 CLEANING**

- A. Clean dirt and debris from panelboard enclosures and components according to manufacturer's instructions.
- B. Repair scratched or marred exterior surfaces to match original factory finish.

**END OF SECTION**